

SmartOnline 120V 1.5kVA 1.35kW Double-Conversion UPS, Tower, Extended Run, Network Card Options, LCD, USB, DB9

MODEL NUMBER: SU1500XLCD





Description

Do you need to protect small- to medium-size servers, networking equipment and telecom systems against data loss, downtime and equipment damage due to power outages, voltage fluctuations and transient surges? Tripp Lite's SU1500XLCD SmartOnline® Tower UPS System is the solution! Featuring a 1500VA/1350W capacity and true on-line operation with pure sine wave output and zero transfer time to battery, it provides the highest level of power protection for mission-critical equipment. The SU1500XLCD's large internal battery set supports connected equipment during blackouts, and runtime is expandable with optional external battery packs BP48V60RT-3U and BP48V27-2US, sold separately. The SU1500XLCD has 6 5-15R outlets, including 2 load banks of 3 outlets each that are individually controllable to reboot select equipment on demand or maximize battery runtime for mission-critical equipment. USB and DB9 communication ports support messaging of detailed UPS operational parameters and line power status. PowerAlert UPS management software is available via free download. The SU1500XLCD also accepts an optional network management card. It comes backed by \$250,000 of Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only).

Features

Ideal for Protection of Mission-Critical EquipmentThe SU1500XLCD provides true on-line operation, reliable battery backup and comprehensive power management capability in a compact tower form factor. Featuring a 1500VA/1350W capacity, 6 5-15R outlets, a 10-ft. cord with standard 5-15P plug, USB/DB9 ports and a slot for an optional network management card, SU1500XLCD offers a complete power protection solution for small- to medium-size servers, storage devices, telecom systems and other mission-critical equipment.

True On-Line Operation with Pure Sine Wave Output and Zero Transfer TimeThe SU1500XLCD provides the highest level of protection available for mission-critical equipment. It actively converts raw incoming AC power to DC, then re-converts it back to regulated, filtered AC output with a pure sine wave, completely isolating connected components from all power problems. Zero transfer time between AC and battery operation maintains continuous output and further protects connected equipment from the disruptive effects of blackouts and severe low-voltage conditions. Sine wave output guarantees compatibility with all equipment types.

Individually Controllable OutletsThe SU1500XLCD includes 2 load banks of 3 outlets each that are individually controllable via a software interface for remote reboot of locked-up equipment or load shedding to maximize battery backup time for mission-critical equipment.

Highlights

- 1500VA / 1.5kVA / 1350 watt on-line double-conversion tower UPS
- 100/110/120/127V 50/60Hz output, 97% efficiency economy mode option
- Interactive LCD with 10 selectable screens of UPS and site power data
- USB, RS232 & EPO ports, slot for network management card options
- Expandable runtime, Hotswappable batteries
- 2 independently switchable load banks
- NEMA 5-15P input; 6 5-15R outlets
- To use the Auto Probe feature, this product requires a WEBCARDLX network interface (sold separately) running LX firmware update 15.5.2 or later

Package Includes

- SU1500XLCD SmartOnline® Tower UPS System
- USB, DB9 and EPO Cabling
- Owner's Manual



Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

Reliable, Expandable Battery BackupUPS battery backup keeps connected equipment operational through short power failures, and provides time to save data and perform an orderly system shutdown in case of a prolonged blackout. The SU1500XLCD features a large internal battery set that provides 14 minutes of battery support for a half load (675 watts) and 4.5 minutes for a full load (1350 watts). Intelligent battery management system extends battery life. During normal operation, incoming utility power keeps the UPS battery fully charged so that backup power will always be available if needed. For mission-critical applications demanding continuous uptime, the fully scalable SU1500XLCD can provide expandable runtime with optional external battery packs BP48V60RT-3U and BP48V27-2US, sold separately.

High Power Factor and Highly Efficient Operation Reduces BTU OutputThe SU1500XLCD features a high 0.9 power factor and an optional, highly efficient economy mode setting that can significantly reduce a facility's energy costs. In economy mode, the UPS operates with 97% efficiency, minimizing heat output, reducing cooling requirements and consuming less electricity.

AC Line and Tel/Ethernet Surge SuppressionA sudden power surge or spike can damage or destroy electronic components and wipe out irreplaceable data. The SU1500XLCD features a 570-joule surge suppression rating to protect connected components and data from the harmful effects of power surges. One set of tel/Ethernet (RJ45) jacks provides surge protection for a standard phone or network connection (cable not included).

EMI/RFI Line Noise FilteringVarious electrical and radio sources can cause disruptive interference on the AC line. This line noise is a common cause of incremental hardware damage, data corruption and audio/video performance problems. The SU1500XLCD incorporates technology that filters out disruptive line noise, preventing it from affecting your equipment.

LCD Screen and Audible AlarmThe SU1500XLCD features a front-panel LCD screen that enables IT personnel to monitor line power, on-line mode, bypass mode, on-battery, overload, battery low, replace battery and fault status information. It is supplemented by an audible alarm that signals UPS startup, power failure, low battery, overload, UPS fault and remote shutdown conditions.

USB/DB9 Ports, SNMP Capability and Included PowerAlert SoftwareSU1500XLCD includes HIDcompliant USB interface that enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. USB and DB9 ports enable data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from <u>www.tripplite.com/poweralert</u>. Compatible with Tripp Lite UPS management card options TLNETCARD, WEBCARDLX, SNMPWEBCARD, MODBUSCARD and RELAYIOCARD.

Emergency Power Off (EPO) CapabilityThe SU1500XLCD features an EPO interface port that supports emergency shutoff in large facilities (cable included).

Peace of MindThe SU1500XLCD comes with \$250,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only) for connected equipment.

Specifications

OVERVIEW		
UPC Code	037332174642	
UPS Type	On-Line	
INPUT		
Rated input current (Maximum Load)	12A	
Nominal Input Voltage(s) Supported	100V AC; 110V AC; 120V AC; 127V AC	



Nominal Input Voltage Description 120V factory default UPS Input Connection Type 5-15P Input Circuit Breakers 15A UPS Input Cord Length (ft.) 10 UPS Input Cord Length (m) 3.1 Recommended Electrical Service 15A 120V Input Phase Single-Phase OUTPUT Output Volt Amp Capacity (VA) Output Volt Amp Capacity (VA) 1.5 Output Watt Capacity (kVA) 1.5 Output Watt Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulatic / conversion mode (1271/20V 945 wats, 115V 851 wats, 110V 804 wats, 100V 756 wats). OVEFLOAD CAPACITY: Supports inverter operating up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and requeurey are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Input Circuit Breakers 15A Input Cord Length (ft.) 10 UPS Input Cord Length (m) 3.1 Recommended Electrical Service 15A 120V Input Phase Single-Phase OUTPUT Output Volt Amp Capacity (VA) Output Capacity (kVA) 1.5 Output Watt Capacity (Watts) 1350 Output KW Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulatic / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously. 125% load for 3 minutes; 150 load for 0.5 seconds and s150% load for 0.5 seconds before switching to SPMASS (when bypass input voltage and frequency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
UPS Input Cord Length (ft.) 10 UPS Input Cord Length (m) 3.1 Recommended Electrical Service 15A 120V Input Phase Single-Phase OUTPUT 0utput Volt Amp Capacity (VA) Output Capacity (kVA) 1.5 Output Watt Capacity (kVA) 1.5 Output Watt Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load of 0.5 seconds before switching to BYPASS (when bypass input voltage or frequency are OUTSIDE bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
UPS Input Cord Length (m) 3.1 Recommended Electrical Service 15A 120V Input Phase Single-Phase OUTPUT 0 Output Volt Amp Capacity (VA) 1500 Output Capacity (kVA) 1.5 Output Capacity (kVA) 1.5 Output Watt Capacity (Watts) 1350 Output KW Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and requency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Recommended Electrical Service 15A 120V Input Phase Single-Phase OUTPUT Output Volt Amp Capacity (VA) 1500 Output Capacity (kVA) 1.5 Output Capacity (Watts) 1350 Output Watt Capacity (WW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 10V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 0.5 seconds before switching to BYPASS (when bypass input voltage and requency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Input Phase Single-Phase OUTPUT Output Volt Amp Capacity (VA) 1500 Output Capacity (kVA) 1.5 Output Capacity (kVA) 1.5 Output Watt Capacity (Watts) 1350 Output KW Capacity (kW) 1.35 Output Capacity (by) 1.35 Output Capacity (by) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulated / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 3 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and requency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
OUTPUT Output Volt Amp Capacity (VA) 1500 Output Capacity (kVA) 1.5 Output Watt Capacity (Watts) 1350 Output KW Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and requency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Output Volt Amp Capacity (VA) 1500 Output Capacity (kVA) 1.5 Output Watt Capacity (Watts) 1350 Output KW Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and frequency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Output Capacity (kVA) 1.5 Output Watt Capacity (Watts) 1350 Output kW Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and frequency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Output Watt Capacity (Watts) 1350 Output kW Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and frequency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Output kW Capacity (kW) 1.35 Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and frequency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Output Capacity Details ON LINE MODE: Maximum output capacity rating is reduced to 1215W (115V), 1148W (110V) and 1080W (100V) FREQUENCY REGULATION / CONVERSION MODE: Maximum output ratings are reduced in frequency regulation / conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and frequency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
/ conversion mode (127/120V 945 watts, 115V 851 watts, 110V 804 watts, 100V 756 watts). OVERLOAD CAPACITY: Supports inverter operation up to 105% load continuously, 125% load for 3 minutes; 150 load for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and frequency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE bypass limits) Power Factor 0.9	ts). % load for 3 minutes; 150% bypass input voltage and
Ioad for 30 seconds and >150% load for 0.5 seconds before switching to BYPASS (when bypass input voltage and frequency are WITHIN bypass limits) or SHUTDOWN (when bypass input voltage or frequency are OUTSIDE Power Factor 0.9	bypass input voltage and
Crest Factor 3:1	
Nominal Voltage Details 120V default	
Frequency Compatibility 50 / 60 Hz; Supports 50 to 60 Hz and 60 to 50 Hz conversion	
Frequency Compatibility Details ON LINE MODE: Output frequency is automatically configured to match nominal input frequency on startup; Output matches input frequency when +/-5Hz of nominal; Output is regulated to +/-0.05Hz when input frequency exceeds +/-5Hz of nominal. UPS switches to battery mode when input frequency is below 40Hz or above 70Hz. FREQUENCY REGULATION / CONVERSION MODE: Output is regulated to +/-0.05Hz of selected output frequency when input is 40 to 70Hz; UPS switches to battery mode when input frequency is below 40Hz or above 70Hz. BATTERY MODE: Output is regulated to +/-0.05Hz of selected nominal.	input frequency exceeds above 70Hz. of selected output frequency
Output Voltage Regulation (Line +/- 2%	
Output Voltage Regulation (Economy Line Mode) +/- 10%	
Output Voltage Regulation (Battery Mode) +/- 3%	
Load Management Receptacles Two switchable three-outlet load banks	
Output AC Waveform (AC Mode) Pure Sine wave	
Output AC Waveform (Battery Mode) Pure Sine wave	
Nominal Output Voltage(s)100V; 110V; 115V; 120V; 127V	
Output Receptacles (6) 5-15R	
Individually Controllable Load Banks Yes	



BATTERY		
Battery Type	Valve Regulated Lead Acid (VRLA)	
Full Load Runtime (min.)	4.5 min. (1350w)	
Half Load Runtime (min.)	14 min. (675w)	
Expandable Battery Runtime	Extended runtime supported via optional external battery packs	
Expandable Runtime	Yes	
Expandable Runtime Description	External battery configurations require the use of Tripp Lite's External Battery Configuration Software, see manual for details	
External Battery Pack Compatibility	<a class="productLink" href="//www.tripplite.com/External-48V-2U-Rack-Tower-Battery-Pack-for-UPS-
Systems~BP48V27-2US">BP48V27-2US (multi-pack compatible); <a <br="" class="productLink">href="//www.tripplite.com/External-48V-3U-Rack-Tower-Battery-Pack-Enclosure-DC-Cabling-select-UPS- Systems~BP48V60RT-3U">BP48V60RT-3U-Rack-Tower-Battery-Pack-Enclosure-DC-Cabling-select-UPS- Systems~BP48V60RT-3U">BP48V60RT-3U-Rack-Tower-Battery-Pack-Enclosure-DC-Cabling-select-UPS-	
DC System Voltage (VDC)	48	
Battery Recharge Rate (Included Batteries)	Less than 3 hours from 10% to 90% (typical, full load discharge)	
Battery Access	Battery access door	
Internal UPS Replacement Battery Cartridge	<a class="productLink" href="//www.tripplite.com/UPS-Replacement-48VDC-Battery-Cartridge~RBC48-
SUTWR">RBC48-SUTWR	
Battery Replacement Description	Hot-swappable, user replaceable batteries	
VOLTAGE REGULATION		
Voltage Regulation Description	Online, double-conversion power conditioning	
Overvoltage Correction	2% output voltage regulation during overvoltages to 150	
Undervoltage Correction	2% output voltage regulation during undervoltages to 55V (33% load), 70V (70% load), 100V (100% load)	
USER INTERFACE, ALERTS & CONTROLS		
Front Panel LCD Display	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, frequency, operating mode, alarm function and a variety of additional options	
Switches	2 switches control off/on power status and alarm-cancel/self-test operation	
Alarm Cancel Operation	Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available	
Audible Alarm	Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions	
SURGE / NOISE SUPPRESSION		
UPS AC Suppression Joule Rating	570	
UPS AC Suppression Response Time	Instantaneous	
UPS Dataline Suppression	1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet	
EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		



Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

[
Primary Form Factor	Tower	
Cooling Method	Fan	
Installation Form Factors Supported with Included Accessories	Tower	
Primary UPS Depth (mm)	495	
Primary UPS Height (mm)	259	
Primary UPS Width (mm)	229	
Shipping Dimensions (hwd / in.)	14.80 x 12.90 x 23.30	
Shipping Dimensions (hwd / cm)	37.59 x 32.77 x 59.18	
Shipping Weight (lbs.)	55.00	
Shipping Weight (kg)	24.95	
UPS Housing Material	Steel	
UPS Power Module Dimensions (hwd, cm)	25.91 x 22.86 x 49.53	
UPS Power Module Dimensions (hwd, in.)	10.2 x 9 x 19.5	
UPS Power Module Weight (kg)	23.72	
UPS Power Module Weight (lbs.)	52.3	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	512	
AC Economy Mode BTU / Hr. (Full Load)	142	
Battery Mode BTU / Hr. (Full Load)	814	
AC Mode Efficiency Rating (100% Load)	90%	
AC Economy Mode Efficiency Rating (100% Load)	97%	
Audible Noise	< 50.5 dB at front side 1m	
Operating Elevation (m)	Up to 3000m	
COMMUNICATIONS		
Network Management Cards	SNMPWEBCARD; <a class="productLink" href="//www.tripplite.com/Web-Management-Accessory-Card-
SmartPro-SmartOnline-UPS-Systems~TLNETCARD">TLNETCARD ; <a <br="" class="productLink">href="//www.tripplite.com/Web-Management-Accessory-Card-WEBCARDLX">WEBCARDLX ; MODBUSCARD ; <a <br="" class="productLink">href="//www.tripplite.com/Programmable-Relay-I-O-Card~RELAYIOCARD">RELAYIOCARD ; & href="//www.tripplite.com/Programmable-Relay-I-O-Card~RELAYIOCARD">RELAYIOCARD <a <br="" class="productLink">href="//www.tripplite.com/Programmable-Relay-I-O-Card~RELAYIOCARD">RELAYIOCARD</a 	



Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 and contact closure communications
For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at https://www.tripplite.com/poweralert
USB and DB9 cabling included
Supports Watchdog application, OS and hard-reboot restart options for remote applications
Network management card optional
Contact closure; DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface; USB (HID enabled)
Zero transfer time (0 ms.) in online, double-conversion and frequency regulation / conversion modes
55V (33% load), 70V (70% load), 100V (100% load)
150
Cold-start operation supported
Auto Probe Monitoring and Reboot (requires WEBCARDLX); Automatic inverter bypass; Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Remote management; Sine wave output; Surge/noise protection; Zero transfer time
High efficiency economy mode operation; Individually controllable load banks; Schedulable daily hours of economy mode operation
CSA (Canada); NOM (Mexico); UL 1778
RoHS; FCC Part 15 Class A (USA)
2-year limited warranty
\$250,000 Ultimate Lifetime Insurance

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies