Gap Pad[®] 3000S30

Features and Benefits

- Thermal conductivity = 3.0 W/mK
- Low S-Class thermal resistance at very low pressures
- Conformable low hardness
- Designed for low pressure applications
- · Fiberglass reinforced for puncture, shear and tear resistance



Gap Pad 3000S30 is an all-new, high performance (3W/m-K) thermally conductive gap filling material. In addition to a high thermal conductivity value, Gap Pad 3000S30 offers exceptionally low interfacial resistances to adjacent surfaces. Featuring a soft, very low hardness specifically designed to comply to unique contours and topography, Gap Pad 3000S30 is ideal for fragile components. The material is reinforced allowing for easy part placement and handling. Gap Pad 3000S30 is supplied with protective liners on both sides.

Note: Resultant thickness is defined as the final gap thickness of the application.



Thermally Conductive, Reinforced, Soft "S-Class" Gap Filling Material

TYPICAL PROPERTIES OF GAP PAD 3000S30			
PROPERTY	IMPERIAL VALUE	METRIC VALUE	TEST METHOD
Color	Light Blue	Light Blue	Visual
Reinforcement Carrier	Fiberglass	Fiberglass	
Thickness (inch) / (mm)	0.010 to 0.125	0.254 to 3.175	ASTM D374
Inherent Surface Tack (1 or 2 sided)	2	2	
Density (g/cc)	3.2	3.2	ASTM D792
Heat Capacity (J/g-K)	1.0	1.0	ASTM C351
Hardness 10-20 mil (Shore 00) (1)	55	55	ASTM D2240
Hardness 40-125 mil (Shore 00) (1)	30	30	ASTM D575
Young's Modulus (psi) / (kPa) (2)	26	180	ASTM D575
Continuous Use Temp (°F) / (°C)	-76 to 392	-60 to 200	
ELECTRICAL			
Dielectric Breakdown Voltage (Vac)	2500 min	2500 min	ASTM D149
Dielectric Constant (1000 Hz)	6.0	6.0	ASTM D150
Volume Resistivity (Ohm-meter)	8.510	8.510	ASTM D257
Flame Rating (pending)	94 V-O	94 V-O	U.L.
THERMAL			
Thermal Conductivity (W/m-K)	3.0	3.0	ASTM D5470
 One second delay value Shore 00 hardness scale. 	-		

2) Young's Modulus, calculated using 0.01 in/min. step rate of strain with a sample size of 0.79 inch². For more information on Gap Pad modulus, refer to Bergquist Application Note #116.

Typical Applications:

- Processors
- Server S-RAMs
- Mass storage drives
- Power conversion
- Wireline/wireless communications hardware

Configurations Available:

- Die cut parts in any shape or size, separated or in sheet form
- Custom sizes available contact Bergquist Product Management

Building a Part Number



Standard Options

example

Notebook computers

BGA packages

NA = Selected standard option. If not selecting a standard option, insert company name, drawing number, and revision level

08|6 =Standard sheet size $8" \times |6"$. 00 = Custom configuration

02 = Naturally tacky both sides

Standard thicknesses available: 0.010", 0.015", 0.020", 0.040", 0.060", 0.080", 0.100", 0.125

GP3000S30 = Gap Pad 3000S30

Note: To build a part number, visit our website at www.bergquistcompany.com.

Gap Pad®: U.S. Patent 5,679,457 and others.



The Bergquist Company

Fax: 952-835-4156

North American Headquarters 18930 West 78th Street Chanhassen, MN 55317 Phone: 800-347-4572

The Bergquist Company - Europe Bramenberg 9a, 3755 BT Eemnes Netherlands Phone: 31-35-5380684 Fax: 31-35-5380295

www.bergquistcompany.com

The Bergquist Company - China Rm. 7C, Aihe Mansion No. 629 Ling Ling Road Shanghai, China 200030 Ph: 86-21-6464-2206 Fax: 86-21-6464-2209

All statements, technical information and recommendations herein are based on tests we believe to be reliable, and All statements, technical information and recommendations merein are based on tests we believe to be reliable, and THE FOLLOWING IS MADE IN LIEU OF ALL WARRANTES, EXPRESSED OR IMPLED, INCL'ODING THE IMPLED WARRANTIES OF MARKETABILITY AND FITNESS FOR PURPOSE. Sellers' and manufacturers' only obligation shall be to replace such quantity of the product proved to be defective. Before using user shall determine the subtability of the product proved to be defective. for its intended use, and the user assumes all risks and liability whatsoever in connection therewith. NEITHER SELLER NOR MANUFACTURER SHALL BE LIABLE EITHER IN TORT OR IN CONTRACT FOR ANY LOSS OR DAMAGE DIRECT. THANGTACTORES SHALL BE LINE EITHER INFLORT OK IN CONTINUE FOR ANY LOSS ON DAMAGE DIRECT, INCIDENTAL OR CONSEQUENTIAL INCLUDING LOSS OF PROFITS OR REVENUE ARISING OUT OF THE USE OR THE INABILITY TO USE A PRODUCT. No statement, purchase order or recommendations by seller or purchaser not contained herein shall have any force or effect unless in an agreement signed by the officers of the seller and manufacturer.