



ELECTRISAVER

Electronic Timer

The Electrisaver is a simple push button electronic timer that saves energy by remembering to switch off an appliance when you might forget!

Suitable for loads up to 3kW, Electrisaver is a perfect boiler override or extension timer and can be used on electrical equipment such as panel heaters, immersion heaters, heated towel rails and oil filled radiators.

Flush or surface mounting

Wiring is simple with easy access terminals

Horstmann. Together, we're in control.

Horstmann. Together, we're in control.



Choose from 15, 30 or 60 minute durations



Choose from 30, 60 or 120 minute durations



Choose from 2, 4 or 6 hour durations

ELECTRISAVER


There are three Electrisaver models which offer preset time periods ranging from 15-60 minutes, 30-120 minutes or 2-6 hours.

Simply press the boost button and walk away, safe in the knowledge that if you forget, Electrisaver won't!

The 3kW rating makes Electrisaver suitable for use with immersion heaters with a range of applications in shops, offices, schools, church halls, student accommodation and all around the home.

- Oil fired radiators
- Towel rails
- Boiler override
- Panel heaters

Schematic wiring diagram



SPECIFICATION

CONTACT RATING
13 Amps 230V AC
Suitable for loads up to 3 kW
SUPPLY
230V 50HZ
POLLUTION DEGREE 2
ENCLOSURE PROTECTION
IP 30
SHOCK PROTECTION

Class 1 LIVE PARTS Enclosed

MAXIMUM OPERATING TEMPERATURE

MINIMUM OPERATING TEMPERATURE 0°C

DIMENSIONS Height: 87mm Width: 87mm

Depth: 16mm flush mounted 51mm surface mounted

MOUNTING

Single gang moulded box (Min. 35mm deep, not supplied)

