

Single joints




Double joints



Constant velocity

The velocity ratio of single universal joints is not constant when the working angle is greater than zero. Their geometry gives rise to sinusoidal fluctuations at the output that increase with the working angle and which vary between:


wcos β and w sec β where w = angular velocity and β = operating angle For example, when the operating angle is 5° , the maximum error is $\pm 0.4\%$; at 7° it is $\pm 0.8\%$, and at 10° it is $\pm 1.5\%$. A motor shaft turning at a constant 1000 rpm, driving through a single universal joint set at an operating angle of 5° , produces an output that fluctuates between 996 rpm and 1004 rpm twice each revolution. The fluctuations are cancelled out when using a double joint or two single joints connected back to back.



To maintain constant velocity ratio, ensure that:

- a) The orientation of two single joints is correct; the inboard forks should align as in double joints.
- b) The working angle of both joints, or both halves of a double joint, is the same.

HUCO Page 2 of 5



MAIN TABLE - DIMENSIONS & ORDER CODES

	Joint										Fasteners		Moment of inertia	Mass
Size	Single JOINT	Double FREE	0D	L	L1	L2	L3	L4	0B1, 0B2 max	Screw	² Torque Nm	Wrench mm	kgm² x 10-8	kg x 10- ³
	101.06	-		19.1	3.3	5.3	0.7		4.76	-	-	-	0.3	0.7
06	103.06	-	7.1	27.2	-	9.3	8.6	-	3.18	M3	0.94	1.5	1.1	3.1
06	-	109.06	7.1	27.2	3.3	5.3	14 7	0.1	4.76	-	M3	-	0.6	1.1
	-	111.06		35.3	-	9.3	16.7 8.1 11.4 - 1 24.6 13.2	3.18	M3	0.94	1.5	1.3	3.5	
	101.09	-		28.5	4.3	8.6	11 /		6.35	-	-	-	4.0	2.7
09	103.09	-	11.1	37.6	-	13.1	11.4	-	5	M	0.94	1.5	13.5	9.3
	-	109.09	11.1	41.7	4.3	8.6	24/	12.2	6.35	-	-	-	5.9	4.5
	-	111.09		50.8	-	13.1	24.0	13.2	5	M3	0.94	1.5	15.3	11.1
	101.13	-		35.6	5.6	10.4	14.8		8	-	-	-	14.3	5.7
13	103.13	-	14.3	46.2	-	15.7	14.0	-	6.35	M3	0.94	1.5	44.6	17.7
13	-	109.13	14.3	51.4	5.6	10.4	30.7	1E 0	8	-	-	-	23.7	9.6
	-	111.13		62.1	-	15.7	30.7	15.9	6.35	M3	0.94	1.5	50.4	21.6
	101.16	-		53.3	8.9	15.2	23.0		11	-	-	-	32.3	12.2
1/	103.16	-	17.5	67.6	-	22.3	23.0	-	10	M4	2.27	2.0	136.0	35
16	-	109.16	17.5	75.5	8.9	15.2	45.0	22.2	11	-	-	-	63.5	19.7
	-	111.16		89.8	-	22.3	45.2	22.2	10	M4	2.27	2.0	178.0	

Materials & Finishes

Forked body members:

Acetal (black)

Cross pieces & headed bore inserts:

Brass BS2874 CZ121

Chromate & passivate finish

Fasteners:

Alloy steel, black oiled

Temperature Range

-20°C to +60°C

	_			 / 4 - 4	A0.01
-	PK.	 H N	100	 (AT 2	-

Joint	Clauste / Devikte	Peak	Ma compen		Tors	ional	Max end	Static break	
Size	Signle / Double	torque Nm	Angular ± deg	Radial ± mm	Rate deg / Nm	Stiffness Nm / rad	loading N	torque NM	
0/	Single	0.11	45	-	19.7	2.9	18	0.45	
06	Double	0.08	90	5.6	81.9	0.7	0	0.34	
00	Single	0.36	45	-	6.8	8.4	38	1.9	
09	Double	0.16	90	9.1	13.3	4.3	0	1.9	

HUCO	Page 3 of 5

10	Single	0.85	45	-	3.2	18.0	67	4.5
13	Double	0.59	90	10.9	8.1	7.1	0	3.4
17	Single	1.6	45	-	1.7	34.0	98	6.8
16	Double	1.3	90	15.5	4.5	12.6	0	6.8

- 1. Recommended datum for cross-pinning/screws, etc.
- 2. Max shaft penetration 3. Maximum recommended tightening torque.
- 4. Values apply with max bores.
- 5. Peak torque. Select a size where Peak Torque exceeds the adjusted torque.
- 6. Torsional stiffness values apply at 50% peak torque with no misalignment, measured shaft-to-shaft with largest standard bores.
- 7. With joints cross-pinned to shafts.
- 8. Couplers can be specified with 'D' bores. See page 4 for details.

ADJUSTED TORQUE

Peak torque values apply when the working angle is zero. Adjusted torque takes account of dynamic loading at the bearings. To find adjusted torque, determine application speed, torque and operating angle,

Then:

- a) multiply speed x working angle
- b) subtract the result from 10000
- c) divide the answer into 10000
- d) apply the result to the application torque.

```
eg. speed = 400 rpm
application torque = 0.1Nm
working angle = 20°
```

Accordingly:

- a) $400 \text{ rpm x } 20^{\circ} = 8000$
- b) 10000 8000 = 2000
- c) 10000 / 2000 = 5
- d) $5 \times 0.1 \text{Nm} = 0.5 \text{Nm}$

Select a joint where Peak Torque exceeds 0.5Nm, ie., size 13 or larger.

Note: To remain within the capacity of the joint, the result of speed x working angle must be less than 10000.

	Joint		0B1,	OB2. Tolera	inces Refs. 101	& 109+0.0	04/-0.01mn	n, Refs. 103 & 1	111 +0.03/-	0mm	
Size	Ref	3	3.175	4	4.763	5	6	6.350	8	9.525	1
06	101 & 109	•	•	•	•						
06	101 & 111	0	0								
00	101 & 109			•	•	•	•	•			
09	101 & 111	0	0	0	0	0					
	101 & 109						•	•	•		
13	101 & 111			0	0	0	0	0			
1.	101 & 109								•	•	
16	101 & 111						0	0	0	0	(
E	Bore ref.	14	16	18	19	20	22	24	28	31	3

Diameters for which a bore adaptor is shown can be adapted to smaller shaft sizes.

Larger Sizes

Osleeved bores

moulted bores

HUCO Page 4 of 5

MAIN TABLE	- DIMENSIONS &	ORDER CODES
------------	----------------	-------------

Joint	Single	e OD		L1	L2	L3	0B1, 0B2	Moment of inertia	Mass
size	JOINT REF.	OD	_	L1	LZ	LJ	max	x 10-8 x	kg x 10- ³
20	105.20	23.0	62.0	8.0	17.20	28.0	12.70	147	25.7
25	105.25	28.5	74.0	10.0	20.0	34.0	14	463	56
32	105.32	36.5	86.0	10.0	21.0	44.0	20	1339	103

Materials & Finishes

Forked body members:

Acetal (black)

Cross pieces:

Brass BS 2874 CZ122

Chromate & passivate finish

Bore sleeves:

Al. Alloy 2011T3 or T8

Temperature Range

-20°C to +60°c

PERFORMANCE (AT 20°C)

Joint	Peak torque	Ma compen		Tors	ional	Max end	Static break torque
size	Nm	Angular ± deg	<u> </u>	loading N	torque Nm		
20	2.8			0.94	61	138	17
25	5.6	40	-	0.51	112	222	34
32	10.7			0.25	229	334	72

- 1. Recommended datum for cross-pinning/screws, etc.
- 2. Max shaft penetration
- 3. Values apply with max bores.
- 4. Peak torque. Select a size where Peak Torque exceeds the adjusted torque.
- 5. Torsional stiffness values apply at 50% peak torque with no misalignment, measured shaft-to-shaft with largest standard bores.
- 6. With joints cross-pinned to shafts.
- 7. Couplers can be specified with 'D' bores. See page 4 for details.

ADJUSTED TORQUE

Peak torque values apply when the working angle is zero. Adjusted torque takes account of dynamic loading at the bearings. To find adjusted torque, determine application speed, torque and operating angle,

Then:

- a) multiply speed x working angle
- b) subtract the result from 10000
- c) divide the answer into 10000
- d) apply the result to the application torque.

Accordingly:

- a) $400 \text{ rpm x } 20^{\circ} = 8000$
- b) 10000 8000 = 2000
- c) 10000 / 2000 = 5
- d) $5 \times 1Nm = 5Nm$

Select a joint where Peak Torque exceeds 5Nm, ie., size 25 or larger.

Note: To remain within the capacity of the joint, the result of speed x working angle must be less than 10000.

HUCO Page 5 of 5

STANDARD BO	RES										
Initial Cine					0B1, 0)B2 +0.03 / -0N	1M				
Joint Size	9.525	10	12	12.700	14	15.875	16	18	19	19.050	20
20	0	0	0	0							
25			0	0	0						
32						0	0	0	0	0	0
Bore ref.	31	32	35	36	38	41	42	45	46	47	48
Correspor bore ada		257		259			260				261
								mou	ılted bores	o _{slee}	ved bores

Diameters for which a bore adaptor is shown can be adapted to smaller shaft sizes.

